

Feasibility Study Report

For: [REDACTED] ("Customer")

Queue #: 42690-01

Service Location: Gaston County, NC

Total Output: 25 MW

Commercial Operation Date: 12/31/2018



Prepared by:
Orvane Piper, Duke Energy Carolinas

Table of Contents

1.0	Introduction	3
2.0	Study Assumptions and Methodology	3
3.0	Thermal Study Results	4
3.1	NRIS Evaluation	4
3.2	ERIS Evaluation.....	4
4.0	Short Circuit Analysis Study Results.....	5
5.0	Reactive Capability Study Results	5



1.0 Introduction

Following are the results of the Generation Feasibility Study for the installation of 25 MW of generating capacity in Gaston County, NC. This site is located near Cherryville Tie and has an estimated Commercial Operation Date of 12/31/2018. This study includes both Network Resource Interconnection Service (NRIS) and Energy Resource Interconnection Service (ERIS).

2.0 Study Assumptions and Methodology

The power flow cases used in the study were developed from the Duke Energy Carolinas (DEC) internal year 2019 summer peak case. The results of DEC's annual screening were used as a baseline to identify the impact of the new generation. To determine the thermal impact on DEC's transmission system, the new generation was modeled as a new interconnection on the Willow 44 kV line. All cases were modified to include 25 MW of additional generation at the Customer's facility. The economic generation dispatch was changed by adding the new generation and forcing it on prior to the dispatch of the remaining DEC Balancing Authority Area units. The study cases were re-dispatched, solved and saved for use. The impacts of changes in the Generator Interconnection Queue were not evaluated, because it was determined that no earlier queued generators would have a significant impact on the study results.

The NRIS thermal study uses the results of DEC Transmission Planning's annual internal screening as a baseline to determine the impact of new generation. The annual internal screening identifies violations of the Duke Energy Power Transmission System Planning Guidelines and this information is used to develop the transmission asset expansion plan. The annual screening provides branch loading for postulated transmission line or transformer contingencies under various generation dispatches. The thermal study results following the inclusion of the new generation were obtained by the same methods, and are therefore comparable to the annual screening. The results are compared to identify significant impacts to the DEC transmission system.

The ERIS thermal study utilizes a model that includes the new generation with relevant earlier queued projects and associated known upgrades. The new generation economically displaces DEC Balancing Authority Area units. Transmission capacity is available as long as no transmission element is overloaded under N-1 transmission conditions. The thermal evaluation will only consider the base case under N-1 transmission contingencies to determine the availability of transmission capacity. ERIS is service using transmission capacity on an "as available" basis; adverse generation dispatches that would make the transmission capacity unavailable are not identified. The study will also identify the maximum allowable output without requiring additional Network Upgrades at the time the study is performed.

Short circuit analysis is performed by modeling the new generator and earlier queued generation ahead of the new generator in the interconnection queue. Any significant changes in short circuit current resulting from the new generator's installation are identified. Various faults are placed on the system and their impact versus equipment rating is evaluated.

Reactive Capability is evaluated by modeling a facility's generators and step-up transformers (GSUs) at various taps and system voltage conditions. The reactive capability of the facility can be affected by many factors including generator capability limits, excitation limits, and bus voltage limits. The evaluation determines whether sufficient reactive support will be available at the Connection Point. The DEC Facilities Connection Requirements (FCR) for generators connected to the Transmission System requires that the generator must be capable of supplying power factor in the range from .93 lagging (producing

Date: 1/18/2017



VARs) to .97 leading (absorbing VARs) measured at the Connection Point. For more information on generator reactive requirements, reference the 'Generator Power Factor Requirements' document on the DEC OASIS site¹.

Any costs identified in the short circuit current, stability or reactive capability studies are necessary for both ERIS and NRIS service.

3.0 Thermal Study Results

3.1 NRIS Evaluation

No earlier queued projects were deemed to have a material impact on the results of the study.

The following network upgrades were identified as being attributable to the studied generating facility:

Facility Name/Upgrade	Existing Size/Type	Proposed Size/Type	Mileage	Estimated Cost	Lead Time (months)
A. Interconnection Cost				\$1.5 MM	24
B. Upgrade Willow 44 kV Line (Cherryville Tie-Hilltop Tie) and install OPGW ²	336 ACSR	556 ACSR	10.3	\$12 MM	36
CUSTOMER TOTAL COST ESTIMATE				\$13.5 MM	36

3.2 ERIS Evaluation

Under the terms of ERIS service, the full output of the plant can be delivered at the time of the study without causing thermal overload of any DEC facilities. The upgrades required for ERIS service are the same upgrades required for NRIS service. The estimated costs and lead times for these upgrades are identified in section 3.1.

¹ http://www.oatioasis.com/DUK/DUKdocs/Generator_Interconnection_Information.html

² The need to rebuild the Willow 44 kV line is driven by the installation of Optical Ground Wire (OPGW) that would be associated with the Customer's facility; the need to rebuild the Willow 44 kV line is not driven by thermal loading issues. DEC utilizes OPGW for providing a communication path for system protection purposes and at times to populate the Energy Management System with operating data (MW, MVAR, etc.). The 44 kV transmission line the Customer desires to interconnect to uses structures that cannot support the additional weight of OPGW. As a result, the entire 10.3 mile 44 kV transmission line would need to be rebuilt in order to install OPGW. DEC will consider alternative forms of communication proposed by the Customer. Any alternative communication schemes must be presented to and approved by DEC during the Facility Study.



4.0 Short Circuit Analysis Study Results

There are no breakers that need to be replaced as a result of the new generation.

5.0 Reactive Capability Study Results

The Customer proposed installing a 6 MVAR capacitor at its facility; however, the maximum allowable size for a capacitor bank associated with the facility is 5.8 MVAR, which allows the Customer to compensate only for plant losses. At the requested value of 25 MW, the facility meets the reactive capability requirements set forth in DEC's FCR both with and without the capacitor installed and in service. Given these considerations, the level of reactive support supplied by the Customer's facility has been determined to be acceptable at this time. Evaluation of MVAR flow and voltages in the vicinity of Cherryville Tie indicates adequate reactive support exists in the region. The recommended tap setting at the high side of the GSU is 45.1 kV.

Study completed by: _____
Orvane Piper, Duke Energy Carolinas

Reviewed by: _____
Edgar Bell, Duke Energy Carolinas
Director, Transmission Planning Carolinas